



Forcom Technology Co., Ltd.

Tel: +886-2-77296880 Fax: +886-2-27585852

e-mail: info@forcomtech.com.tw

URL: <http://www.forcomtech.com.tw>



2.1A/1A USB Power bank

MODEL NO.: PB6600/ PB7800

Features:

- Sleek, slim profile fashion styling
- High-tech, multi-functional, and compatible with numerous devices
- Can be used to charge for two devices at the same time.
- The Powerbank can be charged via USB or Adaptor through the port IN DC5V.
- Supports iPhone .iPad .iPod as well as most smartphones, such as HTC, Samsung, Google, LG, Blackberry, Nokia, Sony, MP3.PSP and more.
- Multi-USB tips for different devices (Mini USB/ Micro USB/ Sony Eriksson/ Samsung

G600/ Samsung D800/ Apple 30pin/ ϕ 2.0mm DC jack)



Specifications:

- Battery Cell: Rechargeable cell 18650 li-ion



Forcom Technology Co., Ltd.

Tel: +886-2-77296880 Fax: +886-2-27585852

e-mail: info@forcomtech.com.tw

URL: <http://www.forcomtech.com.tw>

- Power Capacity choices:
 - 2200mAh x 3pcs
 - 2600mAh x 3pcs
- Rated Output: DC 5V 1A / 2.1A
- Rated Input: DC 5V 1A
- Battery capacity remaining will display with LED lighting.
 - One lighting of LED show the capacity of battery remain 25%.
 - Two lighting of LED for 50%.
 - Three lighting for 75%
 - Four lighting showing the remaining capacity of battery is 100%.
- Charging time: 6~8 hours

- Cycle life : More than 300 times
- Dimensions: 101.4L(mm) x 61.4W(mm) x 22.5 H(mm)
- Weight: 160g(152g)

Environment.

Temperature.

a. Operation: 0 to 40 Deg C.

b. Storage: -40 to 60 Deg C.

Humidity.

a. Operation: 20-80%.

b. Storage: 10-90%.

Altitude.

From sea level to 10,000Ft.(operation)and 40,000Ft(Non operation).

Mechanical.

Plastic Case: PC

Safety Precaution:

- Do not tamper product. Warranty void if product is found tampered with.
- Check device voltage for compatibility with this product.
- Do not attempt to disassemble Powerbank.
- Store and operate between 0-40°C.
- Do not allow this product to have contact with liquids.
- Do not place this product near a heat source or flame or it may explode.



Forcom Technology Co., Ltd.

Tel: +886-2-77296880 Fax: +886-2-27585852

e-mail: info@forcomtech.com.tw

URL: <http://www.forcomtech.com.tw>

-Do not throw or shake the Powerbank.

-Do not operate the Powerbank if it has been subjected to shock or damage.

-Do not crush or puncture the Powerbank.

-Recharge the Powerbank every 3 months when not in use.

Use soft cloth to clean the exterior. Do not use harsh chemicals or strong cleaning solvents.